

King 4000W Gasoline Digital Inverter Generator

Model KCG-4000i

Features:

- Sine wave digital inverter generator provides stable current to power voltage-sensitive electronics
- Powerful 7.5HP, 4 stroke air cooled OHV engine
- Remote start, single pushbutton electric start or recoil start
- DC USB port; 5V/2.1 Amp. DC output for charging smart phones, tablets or any USB powered equipment
- DC cigarette lighter socket 12V/8Amp DC output
- AC duplex outlet: 120V/20 amp AC output
- AC twist lock outlet 120V/30 amp AC output
- Comes with remote control, 12V battery, spark plug socket and funnel
- CSA & EPA approved

Specifications:

Peak Wattage (starting)	4000W
Running Wattage	3500W
AC Outputs	2 x 120V/20 A 1 x 120V/30A
DC Output	12V (DC 8A)
Engine (OHV)	7.5HP
No load speed	3600 RPM
Displacement (cc)	224
Fuel	Unleaded gas
Fuel Tank (L)	12
Oil Capacity (L)	0.6
Run Time	11-12 hrs
Noise Level	65 dB(A)
Dimensions (lxwxh)	26-1/2" x 16-1/2" x 20"
Weight	110