

King 2000W Gasoline Digital Inverter Generator

Model KCG-2000Gi

Features:

- Sine wave digital inverter generator provides stable current to power voltage-sensitive electronics
- Powerful 4.5HP, 4 stroke air cooled OHV engine
- AC outlet: 120V/16.7 amp AC output
- DC outlet: 12V/8.3A DC output
- Designed for quiet operation suitable for home use, camping and boating
- Economical mode switch adjusts the engine speed based on connected load, for improved fuel consumption
- Low oil shut-off overload and power indicator lights
- AC circuit breaker and reset for safe operation
- Easy start manual recoil starter
- CSA & EPA approved
- Comes with DC cables, spark plug socket, oil fill container, screwdriver and oil drain pipe

Specifications:

Peak Wattage (starting)	2100W
Running Wattage	2000W
AC Outputs	2 (2x120V/16.7A)
DC Output	12V (8.3A)
Engine (OHV)	4.5HP
No load speed	5400 RPM
Displacement (cc)	125
Fuel	Unleaded gas
Fuel Tank (L)	7
Oil Capacity (L)	0.45
Run Time	5-6 hrs
Noise Level	57 dB(A)
Dimensions (lxwxh)	21-1/2" x 11-1/2" x 20"
Weight	58 lbs