

King 11,000W Tri-Fuel Digital Inverter Generator Model KCG-11,000i-TF

Features:

- Sine wave digital inverter generator provides stable current to voltage-sensitive electronics
- This tri-fuel inverter generator can run on gasoline, propane or natural gas giving you the flexibility to choose
- Powerful 18HP, 4 stroke air cooled OHV engine
- Single push button electric start, remote control or recoil start
- DC dual USB ports: 5V/3.1 Amp, DC output for charging smart phones, tablets or any USB powered equipment
- AC duplex outlet: 120V/20 Amp, AC output
- AC twist lock outlet: 120V/240V 30 Amp. AC output
- AC outlet: 120V/240V 50 Amp. AC output
- CSA and EPA approved
- Comes with remote control, propane tank and natural gas connection cables, internal battery charger adaptor, 12V battery and spark plug socket and funnel

Specifications:

Starting/Running Wattage	11.000W/8200W (gasoline)
Starting/Running Wattage	7650W/7380W (propane)
Starting/Running Wattage	6375W/6150W (natural gas)
AC Output (120/240V) Gasoline	68.4 Amp/34.2 Amp
AC Output (120/240V) LPG/NG	61,6 Amp/30.8 Amp/51.6 Amp/25.8 Amp
Engine (OHV)	18 HP
No load speed	3600 rpm
Displacement (cc)	457
Fuel	Gasoline/LPG/Natural Gas
Fuel Tank (L)	27
Oil Capacity (L)	1.1
Run Time (Gas-50%/25% Load)	10.5 hrs/17 hrs
Run Time (Propane- 50%/25% ILoad)	9.8 hrs/14 hrs
Noise Level	68 dB(A)
Assembled Dimensions	30" x 26" x 28-1/2"/210 lbs

(lxwxh)/Weight	
Package Dimensions/Weight	31-3/4" x 26-3/4" x 30-1/8"/240 lbs