

King 2500W Gasoline Digital Inverter Generator

Model KCG-2500i

Features:

- Sine wave digital inverter generator provides stable current to power voltage-sensitive electronics
- Powerful 3 HP, 4 stroke air cooled OHV engine
- Carbon monoxide safety system is designed to detect harmful levels of CO which accumulate within the generator work area and automatically shuts down the generator
- DC USB ports (A & C) 5V DC output for charging smartphones, tablets or any USB powered equipment
- DC Cigarette Lighter Socket: 12V/8 Amp DC output
- AC duplex outlet: 120V/13.3 Amp AC output
- Parallel connectivity between two inverter generators for combined output power (optional parallel cable kit needed)
- Economical mode switch adjusts the for improved fuel consumption
- Low oil shut-off overload and power indicator lights
- Comes with spark plug socket and funnel
- CSA & EPA approved

Specifications:

Peak Wattage (starting)	2500W
Running Wattage	1800W
AC Outputs	1 (2x 120V, 13.3 Amp)
DC Output	12V (8A)
Engine (OHV)	3HP
No load speed	3350 RPM
Displacement (cc)	80
Fuel	Unleaded gas
Fuel Tank (L)	4.2
Oil Capacity (L)	0.35
Run Time	6-8 hrs
Noise Level	64 dB(A)
Dimensions (lxwxh)	19-1/4" x 11-1/2" x 19"
Weight	45 lbs