

King 5000W Dual Fuel Gasoline/Propane Digital Inverter Generator

Model KCG-5000i-DF

Features:

- Sine wave digital inverter generator provides stable current to power voltage-sensitive electronics
- This inverter/generator can run on gasoline or propane giving you the flexibility to choose
- Powerful 8 HP, 4 stroke air cooled OHV engine
- Remote start, single-push button electric start or recoil start
- DC USB port 5V/2.1 Amp. DC output for charging smart phones, tablets or any USB powered equipment
- DC cigarette lighter socket: 12V/8 Amp. DC output
- AC Duplex outlet: 120V/20 Amp AC output
- AC Twist lock outlet: 120V/30 Amp AC output
- Comes with propane tank connection cable, Nema L5-30P/Nema TT30R RV adaptor, remote control, 12V battery, and spark plug socket and funnel
- CSA & EPA approved

Specifications:

Peak Wattage (starting)	5000W
Running Wattage	3700W (gasoline) 3330W (propane)
AC Output (120V) (gasoline/propane)	30.8 Amp/27.5 Amp
DC Output	12V (8A)
Engine (OHV)	8HP
No load speed	3600 RPM
Displacement (cc)	224
Fuel	Unleaded gas & propane
Fuel Tank (L)	12
Oil Capacity (L)	0.6
Run Time	11-12 hrs
Noise Level	65 dB(A)
Dimensions (lxwxh)	26-1/2" x 16-1/2" x 20"
Weight	110 lbs